

Pure Smart Power!

12kVA INVERTER GENERATOR

The newest addition to the Dunlite range!

This Australian made and designed inverter generator is tough, safe, portable, and powerful.

This inverter generator is safe enough to run all your sensitive equipment and powerful enough to use in a wide range of home, recreational and professional uses.

Its NEW inverter technology makes this generator one of the purest power sources around.

FEATURES INCLUDE

2 YEAR
WARRANTY
*Conditions Apply

Centre Point Lift

Reduced noise with
Full Enclosure

Exhaust outlet

Tough
Sturdy Frame

HONDA™
Genuine fuel efficient
GX630 V-Twin engine

40Amp Circuit
Breaker

Pure Sine Wave
Inverter Technology

2 x 15Amp IP66
Weatherproof Outlets

34L Fuel Tank

INVERTER **DGH12i**

POWERED by
HONDA™



POWERED by
HONDA™

Victoria: Head Office

59 Export Drive
Brooklyn VIC 3012
Ph: +61 3 9316 9799
Fax: +61 3 9314 0909

Email: dunlite@wellcross.com.au

New South Wales

Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
Ph: +61 2 9757 5800
Fax: +61 2 9757 5899

Email: nsw@wellcross.com.au

Queensland

Unit 2/55 Christensen Rd
Stapylton QLD 4207
Ph: +61 7 3386 2400
Fax: +61 7 3386 1241

Email: qld@wellcross.com.au

North Queensland

Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
Ph: 0425 226 302

Email: mrussell@wellcross.com.au

Western Australia

Unit 8/235 Camboon Road
Malaga WA 6090
Ph: +61 8 9248 2955
Fax: +61 8 9248 2933

Email: wa@wellcross.com.au

South Australia

Ph: 0417 592 530

Email: bnicholas@wellcross.com.au

Pure Power!

12kVA INVERTER GENERATOR

TECHNICAL SPECIFICATIONS

ENGINE

- **Engine** : Honda GX630 V-Twin
- **Type** : 4-stroke, twin cylinder
- **Start System** : Electric
- **Fuel Type** : Unleaded Petrol
- **Oil Type** : 15W-30
- **Fuel Consumption** : 6L/hr



GENERATOR

- **Rated Frequency** : 50 Hz
- **Rated Voltage** : 240 V
- **Max. Output** : 12 kVA

OTHER

- **Fuel Tank Capacity** : 34 L
- **Noise Level** : 74 dBA/7m
- **Dimensions (LxWxH)** : 876 x 545 x 700 mm
- **Weight** : 160 kg



INVERTER **DGH12i**

POWERED by
HONDA

SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

Victoria: Head Office

59 Export Drive
Brooklyn VIC 3012
Ph: +61 3 9316 9799
Fax: +61 3 9314 0909
Email: dunlite@wellcross.com.au

New South Wales

Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
Ph: +61 2 9757 5800
Fax: +61 2 9757 5899
Email: nsw@wellcross.com.au

Queensland

Unit 2/55 Christensen Rd
Stapylton QLD 4207
Ph: +61 7 3386 2400
Fax: +61 7 3386 1241
Email: qld@wellcross.com.au

North Queensland

Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
Ph: 0425 226 302
Email: mrussell@wellcross.com.au

Western Australia

Unit 8/235 Camboon Road
Malaga WA 6090
Ph: +61 8 9248 2955
Fax: +61 8 9248 2933
Email: wa@wellcross.com.au

South Australia

Ph: 0417 592 530
Email: bnicholas@wellcross.com.au